

## Specifications

<b>Specifications</b>	<b>FX1S-10 MR-DS</b>	<b>FX1S-10 MR-ES/UL</b>	<b>FX1S-10 MT-DSS</b>	<b>FX1S-10 MT-ESS/UL</b>	<b>FX1S-14 MR-DS</b>	<b>FX1S-14 MR-ES/UL</b>	<b>FX1S-14 MT-DSS</b>	<b>FX1S-14 MT-ESS/UL</b>
<b>Max. number inputs/outputs</b>	10	10	10	10	14	14	14	14
<b>Power supply</b>	24 V DC	100-240 V AC	24 V DC	100-240 V AC	24 V DC	100-240 V AC	24 V DC	100-240 V AC
<b>Integrated Inputs</b>	6	6	6	6	8	8	8	8
<b>Integrated Outputs</b>	4	4	4	4	6	6	6	6
<b>Output type</b>	Relay	Relay	Transistor (source Type)	Transistor (source Type)	Relay	Relay	Transistor (source Type)	Transistor (source Type)
<b>Power consumption [W]</b>	6	19	6	19	6.5	19	6.5	19
<b>Weight [Kg]</b>	0.22	0.3	0.22	0.3	0.22	0.3	0.22	0.3
<b>Dimensions (W x H x D) [mm]</b>	60 x 90 x 49	60 x 90 x 75	60 x 90 x 49	60 x 90 x 75	60 x 90 x 49	60 x 90 x 75	60 x 90 x 49	60 x 90 x 75

<b>Specifications</b>	<b>FX1S-20 MR-DS</b>	<b>FX1S-20 MR-ES/UL</b>	<b>FX1S-20 MT-DSS</b>	<b>FX1S-20 MT-ESS/UL</b>	<b>FX1S-30 MR-DS</b>	<b>FX1S-30 MR-ES/UL</b>	<b>FX1S-30 MT-DSS</b>	<b>FX1S-30 MT-ESS/UL</b>
<b>Max. number inputs/outputs</b>	20	20	20	20	30	30	30	30
<b>Power supply</b>	24 V DC	100-240 V AC	24 V DC	100-240 V AC	24 V DC	100-240 V AC	24 V DC	100-240 V AC
<b>Integreated Inputs</b>	12	12	12	12	16	16	16	16
<b>Integreated Outputs</b>	8	8	8	8	14	14	14	14
<b>Output type</b>	Relay	Relay	Transistor (source Type)	Transistor (source Type)	Relay	Relay	Transistor (source Type)	Transistor (source Type)
<b>Power consumption [W]</b>	7	20	7	20	8	21	8	21
<b>Weight [Kg]</b>	0.3	0.4	0.3	0.4	0.35	0.45	0.35	0.45
<b>Dimensions (W x H x D) [mm]</b>	75 x 90 x 49	75 x 90 x 75	75 x 90 x 49	75 x 90 x 75	100 x 90 x 49	100 x 90 x 75	100 x 90 x 49	100 x 90 x 75