

Model Number	FX1N-40 MR-DS	FX1N-40 MR-ES/UL	FX1N-40 MT-DSS	FX1N-40 MT-ESS/UL	FX1N-40 MT	FX1N-60 MR-DS	FX1N-60 MR-ES/UL	FX1N-60 MT-DSS	FX1N-60 MT-ESS/UL	FX1N-60 MT
Integrated Inputs/Outputs	40	40	40	40	40	60	60	60	60	60
Power Supply	12 - 24VDC	100 - 240VAC	12 - 24VDC	100 - 240VAC	100 - 240VAC	12 - 24VDC	100 - 240VAC	12 - 24VDC	100 - 240VAC	100 - 240VAC
Integrated Inputs	24	24	24	24	24	36	36	36	36	36
Integrated Outputs	16	16	16	16	16	24	24	24	24	24
Output Type	Relay	Relay	Transistor (Source)	Transistor (Source)	Transistor (Sink)	Relay	Relay	Transistor (Source)	Transistor (Source)	Transistor (Sink)
Power Consumption (W)	18	32	18	32	32	20	35	20	35	35
Weight (kg)	0.65	0.65	0.65	0.65	0.65	0.8	0.8	0.8	0.8	0.8
Dimen. (W x H x D) mm	130 x 90 x 75	130 x 90 x 75	130 x 90 x 75	130 x 90 x 75	130 x 90 x 75	175 x 90 x 75	175 x 90 x 75	175 x 90 x 75	175 x 90 x 75	175 x 90 x 75